

IC-41PRO

- 80 Channel UHF CB (*)
- Waterproof and dustproof (IP67)
- 5 year warranty on radio
- 18hr typ. operating time with BP280
- Rotary Channel Selector/Squelch control
- Voice announcement of channel number
- VOX capability with optional headset options
- Scrambler capability built in (**)
- Output power 5 Watts (low power 1 Watt)
- Private Channels from 450-520MHz available for commercial users (dealer programmable), requires FASC72U antenna (frequency between 490-520MHz)



(*) 80 Channel UHF CB, 61-63 not present, reserved for future use

(**) Must be enabled by dealer or via CS-41PRO software

Accessories

BP280 Battery, BC213 Battery Charger, BC123SV AC Adaptor, MB133 Belt-Clip & FASC72U Antenna included

Order Code	Description
IC-41PRO	5W, Waterproof 80+ Channel

Batteries	
BP280	Li-Ion 7.2V/2400mAh battery (as supplied)
BP279	Li-Ion 7.2V/1485 mAh
BP278	Li-Ion 7.2V/1130 mAh

Carry Cases	
LC2000C	Leather case with clip
LC2000S	Leather case with swivel
NC2000C	Nylon case with clip Black
NC2000C-OR	Nylon case with clip Orange

Chargers	
BC213	Single drop in rapid charger (as supplied) with BC123SV
BC123SV	Adaptor, AC, for use with BC213 (as supplied)
CP23L	Cigarette lighter cable, for use with BC213
MB130	In Vehicle charging bracket for use with BC213
BC214	6 Way rapid charger includes 6xAD130 charger adaptor & BC157S AC adaptor
AD130	Charger adaptor
BC157S	AC adaptor, for use with BC214
OPC-656	Power supply cable, for use with BC214

Belt Clip

MB133 Aligator type (as supplied)

Programming Equipment

CS-41PRO #32 Dealer programming Software

OPC-478UC USB programming cable

Remote Audio Options

HM153LA Speaker/microphone, ear-piece style with PTT, 90 degree entry
(detachable earpiece)

HM158LA Speaker/microphone, compact & durable body, 90 degree entry
with screw-type (with earphone jack)

HM159LA Noise cancelling microphone, 90 degree entry with screw-type
(with earphone jack)

HM166LA Microphone, Earpiece, 90 degree entry

HM168LWP Waterproof (IP67) speaker microphone

HS94LWP Earhook type

HS95LWP Behind the head headset

HS97 Throat micrpphone (use with VS-4LA or OPC-2004LA)

VS4LA PTT switch cable, required when using HS97

OPC-2004LA Plug adaptor cable VOX operation use with HS97

Spare Antenna

FASC72U UHF flexible antenna (470-520MHz band), As supplied

FASC73US UHF stubby antenna (450-490MHz band)